

Ultra-compact GNSS SiP Module

CS101

CS101 is an ultra-compact single-band multi-constellation GNSS SiP module. It offers high sensitivity, low power consumption, anti-jamming capabilities. CS101 can track multiple GNSS systems simultaneously, including GPS, BDS, GLONASS, Galileo and QZSS, providing users with fast, accurate and high performance positioning experiences.


Featuring with ultra-small size and low power consumption, this module is suitable for wearable devices, trackers and handheld devices, etc.



Technical advantages

- › L1 band, BDS/GPS/GLONASS/Galileo/QZSS
- › Compact Integration: built in LNA, SAW and TCXO
- › Low power consumption
- › Adaptive anti-jamming capability
- › Real-time and predicted A-GNSS
- › Package: LGA53: 4.5x4.5x1.1 (mm)

Product block diagram



Product Specifications

Performance Index

Supported GNSS Constellation	GPS: L1C/A BDS: B1I, B1C GLONASS: G1 Galileo: E1B/C QZSS: L1C/A
Position Accuracy(CEP) ^①	Horizontal accuracy: 2m Velocity accuracy: 0. 1m/s
TTF ^②	Cold start: 26s Hot start: 1s Re-acquisition: 2s
Sensitivity ^{③④}	Cold start: -149dBm Hot start: -155dBm Tracking: -165dBm Re-acquisition: -159dBm
Power consumption ^⑤	Tracking : 13mA @3.3V (DCDC mode) Aquisition: 15.5mA @3.3V (DCDC mode)
Update rate	1Hz ~ 5Hz
Data format	NMEA-0183, ICOE protocol

Others

Main power supply	1. 8V~3. 6 V
Backup power supply	1. 7V~3. 6 V
Communication interface	UARTx2
Operating temperature	-40°C~+85°C
Storage temperature	-40°C~+85°C
Reliability and certification	Complies with JEDEC standards RoHS and REACH requirements
Package	LGA53: 4. 5x4. 5x1. 1 (mm)
Application restrictions	Acceleration≤4g Altitude<18,000m Velocity<515m/s

Note:

- ① Simulated linear motion at constant velocity (33 m/s)
- ② Instrument-measured satellite signal strength: -130 dBm
- ③ C/N0 of 41 dB-Hz achieved at -130 dBm signal level
- ④ With external Low-Noise Amplifier (LNA) implementation
- ⑤ The test result is based on DCDC mode and Vmain for 1. 8V supply

*This feature is still under development.

Final performance parameters will be documented in the subsequent product release specification.

Application scenarios



Handheld devices



Trackers



Smart watches